20 STERN AVE. SPRINGFIELD, NEW JERSEY 07081 U.S.A.

# 2SB643, 2SB644

Silicon PNP epitaxial planer type


For low-power general amplification Complementary to 2SD638 and 2SD639

Absolute Meximum Petinge (T. asic)

### Features

 M type package allowing easy automatic and manual insertion as well as stand-alone fixing to the printed circuit board.

Parameter		Symbol	Ratings	Unit	
Collector to	2SB643	17	-30		
base voltage	2SB644	V <sub>CBO</sub>	-60	v	
Collector to	2SB643		-25		
emitter voltage	2SB644	V <sub>CEO</sub>	-50	v	
Emitter to base voltage		V <sub>EBO</sub>	-7	v	
Peak collector current		I <sub>CP</sub>	-1	Α	
Collector current		l <sub>c</sub>	- 0.5	A	
Collector power dissipation		P <sub>C</sub>	600	mW	
Junction temperature		Tj	150	۰C	
Storage temperature		T <sub>stg</sub>	-55 ~ +150	•C	



#### Electrical Characteristics (Ta=25°C)

Parameter		Symbol	Conditions	min	typ	max	Unit
Collector cutoff current		l <sub>CBO</sub>	$V_{CB} = -20V, I_E = 0$			-100	nA
		I <sub>CEO</sub>	$V_{CE} = -20V, I_{B} = 0$			-1	μΑ
Collector to base	2SB643		$I_{\rm C} = -10\mu {\rm A}, I_{\rm E} = 0$	-30			v
voltage	2SB644	V <sub>сво</sub>		-60			
Collector to emitter	2SB643	•	$I_{\rm C}$ = -2mA, $I_{\rm B}$ = 0	-25			v
voltage	2SB644	V <sub>CEO</sub>		-50			
Emitter to base voltage		V <sub>EBO</sub>	$I_{\rm E} = -10\mu A, I_{\rm C} = 0$	-7			v
Forward current transfer ratio		h <sub>FE1</sub> *1	$V_{CE} = -10V, I_C = -150mA^{*2}$	85		340	
		h <sub>FE2</sub>	$V_{CE} = -10V, I_C = -500mA^{*2}$	40	90		
Collector to emitter saturation voltage		V <sub>CE(sat)</sub>	$I_{\rm C} = -300 {\rm mA}, I_{\rm B} = -30 {\rm mA}^{*2}$		- 0.35	- 0.6	v
Transition frequency		f <sub>T</sub>	$V_{CB} = -10V$ , $I_E = 10mA$ , $f = 200MHz$		200	····	MHz
Collector output capacitance Co		C <sub>ob</sub>	$V_{CB} = -10V, I_E = 0, f = 1MHz$		6	15	pF

\*2 Pulse measurement

#### \*1h<sub>FE1</sub> Rank classification

Rank	Q	R	S
h <sub>FEI</sub>	85 ~ 170	120 ~ 240	170 - 340

NJ Semi-Conductors reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by NJ Semi-Conductors is believed to be both accurate and reliable at the time of going to press. However, NJ Semi-Conductors assumes no responsibility for any errors or omissions discovered in its use. NJ Semi-Conductors encourages customers to verify that datasheets are current before placing orders.



# **Quality Semi-Conductors**

## TELEPHONE: (973) 376-2922 (212) 227-6005 FAX: (973) 376-8960

Unit: mm