

New Jersey Semi-Conductor Products, Inc.

20 STERN AVE.
SPRINGFIELD, NEW JERSEY 07081
U.S.A.



TELEPHONE: (973) 376-2922
(212) 227-6005
FAX: (973) 376-8960

26MT

Three Phase Bridge Rectifier, 25A

Features

- Easy connections
- Surge capability up to 500A
- Low thermal resistance
- High thermal conductivity
- Electrically insulated case
- Center hole fixing



Voltage Ratings ($T_c = 25^\circ\text{C}$ unless otherwise noted)

| Type number | Voltage code | V_{RRM} , Max. repetitive peak reverse voltage (V) | V_{RSM} , Max. non-repetitive peak reverse voltage (V) | I_{RRM} max @ T_j max (mA) |
|-------------|--------------|--|--|--------------------------------|
| 26MT | 80 | 800 | 900 | 2.0 |
| | 100 | 1000 | 1100 | |
| | 120 | 1200 | 1300 | |
| | 140 | 1400 | 1500 | |
| | 160 | 1600 | 1700 | |

Electrical Specifications ($T_c = 25^\circ\text{C}$ unless otherwise noted)


| Parameters | Conditions | Symbol | Values | Units |
|---|--|-----------|--------|-------|
| Maximum DC output current | $T_c = 70^\circ\text{C}$ | I_o | 25 | A |
| Forward surge current (non-repetitive), one cycle | @ 50 Hz | I_{FSM} | 360 | A |
| Maximum forward voltage drop | $I_{FM} = 40\text{A}$, $T_j = 25^\circ\text{C}$ | V_{FM} | 1.26 | V |
| RMS isolation voltage | $f = 50\text{Hz}$, $t = 1\text{ms}$, all terminals shorted | V_{ISO} | 2500 | V |

Thermal and Mechanical Specifications ($T_c = 25^\circ\text{C}$ unless otherwise noted)

| Parameters | Symbol | Values | Units |
|--|---------------|---------------|-------|
| Maximum operating junction temperature range | T_j | - 55 to + 150 | °C |
| Maximum storage temperature range | T_{STG} | - 55 to + 150 | °C |
| Junction to case | $R_{th(j-c)}$ | 1.2 | °C/W |
| Mounting torque ±10% | F | 2.0 | Nm |
| Approximate weight | W | 20 | g |

26MT

Package Outline



ALL DIMENSIONS IN MM

Ordering Table

| 26 | MT | 160 |
|-----------|-----------|------------|
| 1 | 2 | 3 |

1 – Current Rating, $I_{F(AV)}$ (26 = 25A, Average)

2 – Three-Phase Bridge

3 – Voltage = code x 10 = V_{RRM}